

## PATENT

AMENDMENTS TO THE CLAIMS

Please amend the claims as indicated in the following listing of all claims:

1. (Currently amended) A frequency divider comprising:  
a sequence of divide stages coupled to selectively provide a plurality of different divide ratios; and  
at least one multiplexer coupled to selectively feed back the output of ~~a first~~ at least one of the divide stages stage to an input of ~~[[a]]~~ another of the divide stages stage earlier in the sequence of divide stages; and  
a duty-cycle stage coupled to at least one of the divide stages to correct a duty cycle of an output of at least one of the divide stages having an odd divide ratio.
2. (Original) The frequency divider of claim 1 further comprising at least one input coupled to receive a programmable control signal indicating which of the plurality of different divide ratios to apply.
3. (Currently amended) The frequency divider of claim 1 further comprising an input to receive a signal to be divided and wherein respective ones of the divide stages include a clock input coupled to the signal to be divided.
4. (Canceled)
5. (Canceled)
6. (Currently amended) The frequency divider of claim ~~[[5]]~~ 1, wherein the duty-cycle stage includes:  
a first input to receive a first signal having an unbalanced duty cycle;  
a second input to receive a second signal, wherein the second signal is a delayed version of the first signal; and  
logic to generate a signal having a balanced duty cycle using the first signal and the second signal.

## PATENT

7. (Currently amended) The frequency divider of claim 1 wherein respective ones of the divide stages include an activation input coupled to receive an activation signal to selectively turn off one or more ~~respective~~ divide stages if the one or more ~~respective~~ divide stages are not used for a selected divide ratio.

8. (Currently amended) The frequency divider of claim 1 further including self-correction logic coupled to outputs of at least some of the divide stages to correct an abnormal state of the frequency divider.

9. (Currently amended) The frequency divider of claim 8 further including a latch circuit in at least one of the divider stages, the latch circuit including:

~~one or more portions of the~~ self-correction logic; and  
selection circuitry implementing the at least one multiplexer.

10. (Canceled)

11. (Currently amended) A frequency divider comprising:  
a plurality of divide stages programmably coupled to provide a plurality of different divide ratios; and  
wherein respective ones of the divide stages include an activation input coupled to receive an activation signal to selectively turn off one or more of the respective divide stages if the one or more of the respective divide stages are not used for a selected divide ratio.

12. (Currently amended) The frequency divider of claim 11 further comprising at least one multiplexer coupled to selectively couple an output of a first one of the divide stages stage to an input of a second one of the divide stages stage.

13. (Currently amended) The frequency divider of claim 11 further comprising a duty-cycle stage coupled to correct a duty cycle of an output of at least one of the divide stages ~~outputs~~ having an odd divide ratio.

## PATENT

14. (Original) The frequency divider of claim 13, wherein the duty-cycle stage includes:  
a first input to receive a first signal having an unbalanced duty cycle;  
a second input to receive a second signal, wherein the second signal is a delayed version  
of the first signal; and  
logic to generate a signal having a balanced duty cycle using the first signal and the  
second signal.

15. (Canceled)

16. (Currently amended) The frequency divider of claim 11 further including self-correction logic coupled to outputs of at least some of the divide stages to correct an abnormal state of the frequency divider.

17. (Currently amended) The frequency divider of claim 16 further including a latch circuit, the latch circuit including:  
~~one or more portions of~~ the self-correction logic; and  
selection circuitry implementing a multiplexer.

18. (Canceled)

19. (Original) The frequency divider of claim 11, wherein the plurality of divide stages are programmably coupled to produce an output having a divide ratio selected from the following group of divide ratios: 1/11, 1/9, 1/7, 1/6, 1/5, and 1/4.

20. (Currently amended) A clock generation circuit comprising:  
an input coupled to receive a signal having a first frequency;  
an output coupled to provide a clock signal having a frequency derived from the first frequency;  
a divider coupled to the input and the output, the divider including:  
a sequence of synchronous divide stages to provide a plurality of different divide ratios; [[and]]

## PATENT

one or more multiplexers to selectively feed-back an output of a divide stage to an input of a divide stage earlier in the sequence; and  
wherein respective ones of the divide stages further comprise an activation input coupled to receive an activation signal to selectively turn off respective divide stages if the respective divide stages are not used for a desired divide ratio.

21. (Currently amended) The clock generation circuit of claim 20 wherein the divider further includes a duty-cycle stage coupled to correct a duty cycle of an output outputs of one or more of the divider stages having an odd divide ratio.

22. (Original) The clock generation circuit of claim 21, wherein the duty-cycle stage includes:

a first input to receive a first signal having an unbalanced duty cycle;  
a second input to receive a second signal, wherein the second signal is a delayed version of the first signal; and  
logic to generate a third signal having a balanced duty cycle using the first signal and the second signal.

23. (Canceled)

24. (Currently amended) The clock generation circuit of claim 20 wherein said divider includes self-correction logic coupled to outputs of at least some of the divide stages to correct abnormal states of the divider.

25. (Currently amended) The clock generation circuit of claim 24 wherein said divider further includes a latch circuit in at least one of the divide stages, the latch circuit including:  
~~one or more portions of the~~ self-correction logic; and  
selection circuitry implementing at least one of the one or more multiplexers.

26. (Canceled)

## PATENT

27. (Currently amended) A method comprising:  
providing an input clock to a divider, the divider including a sequence of divide stages  
coupled to selectively provide a plurality of different divide ratios;  
clocking each of the divide stages with the input clock; [[and]]  
selectively feeding back an output of a first one of the divide stages stage to an input of a  
second one of the divide stages stage earlier in the sequence of divide stages; and  
selectively turning off one or more of the divide stages if the one or more divide stages is  
not used for a desired divide ratio.
28. (Original) The method of claim 27 further comprising programming the divider to  
produce a selected divide ratio.
29. (Canceled)
30. (Original) The method of claim 27 further comprising correcting a duty cycle of an  
output produced by the divider.
31. (Currently amended) The method of claim 30, wherein correcting [[a]] the duty  
cycle includes:  
generating a first signal having an unbalanced duty cycle;  
generating a second signal, wherein the second signal is a delayed version of the first  
signal; and  
logically combining the first signal and the second signal to generate an output signal  
having a balanced duty cycle.
32. (Original) The method of claim 27 further including correcting an abnormal state of  
one or more divider stages.
33. (Currently amended) The method of claim 32 wherein correcting [[an]] the  
abnormal state includes:  
latching an output of a selected portion of a correction circuit, wherein the portion is  
selected based, at least in part, on a divide ratio to be achieved.

## PATENT

34. (Currently amended) A circuit comprising:  
means for providing an input clock to a divider, the divider including means for  
selectively providing a plurality of different divide ratios;  
means for clocking each of ~~[[the]]~~ a plurality of divide stages with the input clock;  
[[and]]  
means for selectively feeding back an output of at least one of the divide stages ~~a first~~  
~~divide stage~~ to an input of another of the divide stages ~~a second divide stage~~; and  
means for selectively turning off one or more of the stages of the divider if the one or  
more stages is not used for a desired divide ratio.
35. (Canceled)
36. (Original) The circuit of claim 34 further comprising means for correcting a duty cycle of an output produced by the divider.
37. (Original) The circuit of claim 34 further including means for correcting an abnormal state of one or more stages of the divider.
38. (Original) The circuit of claim 37 wherein the means for correcting an abnormal state includes means for latching an output of a selected portion of a correction circuit, wherein the portion is selected based, at least in part, on a divide ratio to be achieved.
39. (Original) The circuit of claim 34 further comprising means for programming the divider to produce a selected divide ratio.